The Patent Office

GB03/05690

INVESTOR IN PEOPLE

REC'D 10·FEB 2004

WIPO   PCT

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

PRIORITY DOCUMENT

SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Signed   M Clarke

Dated   3 February 2004

Pat... ...rm 1/77

atents A 1977
Rule 16)

PATENTS • DESIGNS
The
Patent
Office
COPYRIGHT • TRADE MARKS

1/77

24DEC02 E772901-3 D02000
P01/7700 0.00-0229829.7

Request for grant of a patent
(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

THE PATENT OFFICE
D
20 DEC 2002
LONDON

The Patent Office

Cardiff Road
Newport
South Wales
NP10 8QQ

1.	Your reference	PDG/AJB/25152GB

20 DEC 2002

2. Patent application number
(The Patent Office will fill in this part)

0229829.7

3. Full name, address and postcode of the or of each applicant *(underline all surnames)*

Snell & Wilcox Limited
6 Old Lodge Place
St Margaret's
Twickenham
Middlesex TW1 1RQ United Kingdom

Patents ADP number *(if you know it)*

If the applicant is a corporate body, give the country/state of its incorporation

U.K.

5579784 003

4. Title of the invention

IMPROVED COMPOSITE DECODING

5. Name of your agent *(if you have one)*

"Address for service" in the United Kingdom to which all correspondence should be sent *(including the postcode)*

MATHYS & SQUIRE
100 Gray's Inn Road
London WC1X 8AL
United Kingdom

Patents ADP number *(if you know it)*   1081001

	Country	Priority application number *(if you know it)*	Date of filing *(day / month / year)*
6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and *(if you know it)* the or each application number			

	Number of earlier application	Date of filing *(day / month / year)*
7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application		

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? *(Answer 'Yes' if:*
   a) *any applicant named in part 3 is not an inventor, or*
   b) *there is an inventor who is not named as an applicant, or*
   c) *any named applicant is a corporate body.*
   See note (d))

YES

Patents Form 1/77

Patents Form 1/77

9. Enter the number of sheets for any of the
   following items you are filing with this form.
   Do not count copies of the same document

           Continuation sheets of this form

           Description   7

           Claim(s)   1

           Abstract   -

           Drawing(s)   11

10. If you are also filing any of the following,
    state how many against each item.

           Priority documents

           Translations of priority documents

           Statement of inventorship and right
           to grant of a patent *(Patents Form 7/77)*

           Request for preliminary examination
           and search *(Patents Form 9/77)*   1

           Request for substantive examination
           (Patents Form 10/77)

           Any other documents
           (please specify)   -

11.   I/We request the grant of a patent on the basis of this application.

               Signature *Mathys & Squire* Date

               MATHYS & SQUIRE   20 December 2002

12. Name and daytime telephone number of
    person to contact in the United Kingdom

               Peter D. Garratt - 020 7830 0000

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

a) If you need help to fill in this form or you have any questions, please contact the Patent Office on 08459 500505.

b) Write your answers in capital letters using black ink or you may type them.

c) If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.

d) If you have answered 'Yes' Patents Form 7/77 will need to be filed.

e) Once you have filled in the form you must remember to sign and date it.

f) For details of the fee and ways to pay please contact the Patent Office.

IMPROVED COMPOSITE DECODING

This invention concerns the decoding of composite colour television signals to colour components.

Composite colour television systems, such as NTSC and PAL are designed so that the luminance and chrominance components of the signal can occupy the same spectrum and yet be separated with acceptable levels of crosstalk. Use of the composite signal for display always requires it to be separated (decoded) into primary colour components (red, green and blue); many other processing operations require at least the separation of the chrominance from the luminance, and often, further decoding of the chrominance.

The choice of decoding method for a particular application depends on the acceptable level of crosstalk between chrominance and luminance, and the degree of distortion to the wanted chrominance and luminance as a result of the separation process. Where images are to be displayed on large screens, or must stand comparison with images derived from film, the very highest level of chrominance and luminance separation is necessary, with negligible crosstalk and distortion.

High quality composite decoders exploit the fact that the chrominance is modulated onto a high-spatial-frequency, moving diagonal carrier, which is unlikely to be replicated by real luminance. By using contributions from several lines and fields it is possible to create comb-filters which allocate different parts of the signal spectrum to luminance and chrominance and so achieve separation with little crosstalk on typical pictures. However, it is frequently necessary to "adapt" the frequency characteristics of the filters in dependence upon the type of picture material, so as to avoid crosstalk or distortion of critical material.

European patent EP1175102 presents a novel method of doing this by using a fast Fourier transform (FFT) to convert the signal into the frequency domain and then investigating the symmetry of the spectrum with respect to subcarrier frequency. Because the chrominance components are amplitude modulated, each Fourier component of the baseband chrominance results in a pair of equal-amplitude sidebands symmetrically disposed about the subcarrier frequency. By comparing each frequency component with the corresponding component which would correspond to the opposite chrominance sideband, it is possible to determine whether the particular component represents luminance or chrominance.

The cited patent does not explain how to apply the technique to NTSC, and is restricted to applications where the signal is sampled at a multiple of the subcarrier frequency.

The present inventor has appreciated that there are a number of improvements which widen the applicability of the prior art, in particular it may be applied to the decoding of NTSC, certain distortions which may exist in the coded signal may be corrected and the processing may be carried out on demodulated chrominance signals at any sampling rate.

The invention consists in one aspect of a method of separating the chrominance and luminance of a composite colour television signal by comparing a first frequency component of the signal with a second frequency component of the signal, the second component having a frequency difference from the colour subcarrier equal and opposite to the frequency difference of the first frequency component from the colour

subcarrier, characterised in that the comparison differs in dependence upon the frequency of the first frequency component.

Suitably, the comparison differs in dependence upon the horizontal spatial frequency of the said first frequency component.

Advantageously, the comparison differs in dependence upon the vertical spatial frequency of the said first frequency component.

Additionally the comparison may differ in dependence upon the temporal frequency of the said first frequency component.

In a further embodiment the comparison may differ in dependence upon horizontal, vertical or temporal differences of a composite signal.

Advantageously the temporal differences may be derived from the output of a chrominance demodulator.

In a further aspect the invention consists of a method of separating the chrominance and luminance of a composite colour television signal by comparing a first frequency component of the signal with a second frequency component of the signal, the second component having a frequency difference from the colour subcarrier equal and opposite to the frequency difference of the first frequency component from the colour subcarrier, wherein the comparison is made between frequency components of demodulated, baseband chrominance signals.

In a yet further aspect the invention consists of a method of correcting distortion of a composite colour television signal in which an upper chrominance sideband is identified and its amplitude corrected by making it equal to the amplitude of the corresponding lower chrominance sideband.

Advantageously the corresponding lower sideband is identified in terms of its horizontal spatial, vertical spatial and temporal frequency co-ordinates.

An example of the invention will now be described with reference to the drawings in which:

First a known decoder will be described to illustrate the deficiencies of the prior art. Referring to Figure 1, a composite PAL signal (1), which has been sampled at four times its colour subcarrier frequency ($4f_{sc}$) is divided (2) into three-dimensional, spatially-overlapping blocks; a window function is applied (3) to each block; and, a three-dimensional FFT is taken (4) of each block.

A three-dimensional block means a block of spatially and temporally contiguous pixels taken from a number of consecutive fields; for example 16 horizontally-adjacent pixels on 16 vertically-adjacent lines on 8 consecutive fields, giving a total of 2048 pixels.

The result of the FFT will be (in the case of the above example) a set of 2048 frequency components defining the block of pixels in terms of horizontal spatial frequency, vertical spatial frequency and temporal frequency. Each component has both an amplitude and a phase value. These components will be processed to remove those due to luminance, so that only the components representing chrominance are input to the inverse FFT (10).

The block (5) determines the magnitude of each component. The divider (6) divides each component by its magnitude so as to normalise it to unit amplitude.

The comparator (8) compares the magnitude of each component with the magnitude of one other component. The other component is selected (by the block (7)) to be the component whose three-dimensional frequency difference from the colour subcarrier frequency is equal and opposite to the component's own frequency difference from the colour subcarrier.

This point is illustrated in Figure 2, which shows how the selection of the corresponding frequency component is made in the vertical and temporal frequency dimensions. As the signal has been sampled vertically (by the line structure) and temporally (by the field structure), the spectrum repeats vertically and temporally as shown. The figure shows the spectral position of the colour subcarrier (f_{sc}) and a frequency component which is to be processed (x). The position of the component with equal and opposite frequency difference is shown as (w). For completeness the figure also shows the position of the (phase alternating) V carrier (V).

Figure 2 shows only the vertical and temporal dimensions; it must be noted that the horizontal dimension of the spectrum must treated in an analogous manner in determining the frequency component (w) which will be selected for the magnitude comparison.

Returning to Figure 1, the block (8) outputs the magnitude of the smaller of the two compared components to the multiplier (9). As explained above the second input to the multiplier is a unity-magnitude component having the phase of the component being processed. The output of the multiplier is thus a modified frequency component having the original phase, but with reduced amplitude if the relevant "subcarrier-reflected" component had smaller amplitude.

All 2048 frequency components in each block are processed in this way and input to the inverse FFT (10), whose output is a filtered block of pixels with luminance frequencies attenuated.

The result of this processing is a three-dimensional block of 2048 chrominance pixels which is windowed in the block (11). This window is chosen so that its combination with the window (3) gives a response which tessellates; i.e. so that when the output blocks are combined (12) there is no amplitude dependency on the position within the block. An example is the use of an identical cosinusoidal function for each window, giving a raised cosine response for the combination.

The output of the block (12) is a modulated chrominance signal which can be subtracted (with appropriate allowance for processing delay) from the composite input

in the block (13) to give separated luminance output (14), and demodulated (15) to give baseband U and V colour-difference outputs (16).

Inspection of Figure 2 shows that, because of the repeating structure of the spectrum, there are certain frequencies which inherently mimic symmetrical, double sideband chrominance. One of these is the phase alternating V-axis carrier; this is fortunate as it is a true chrominance component. Another is the moving diagonal pattern at the position (*a*); this is identical to true subcarrier except that it moves with one third the speed in the opposite direction. A further example is shown at (*b*) and is identical to the V-axis carrier but moving at one third speed in the opposite direction. Both these patterns would give rise to coarse cross-colour when decoded according to the prior art.

A further disadvantage of the prior-art approach becomes apparent when both colour difference signals give rise to a sideband having the same (or very similar) frequency. In this case the magnitude of that component will depend on the relative phase of the two baseband colour difference components and the expected symmetry may not result. This is less likely in PAL because the U and V carriers have different spatio-temporal frequencies. However, in NTSC, where the two colour difference signals are modulated onto the same carrier frequency, this situation may well result from the coding of coloured patterns or textures.

An embodiment of the current invention will now be described with reference to Figure 3. This shows a decoder having the same structure as Figure 1, except that the minimum function (8) of Figure 1 has been replaced by a look-up-table (308).

The table has inputs for the magnitude of the frequency component being processed, the magnitude of the corresponding component symmetrically disposed with respect to subcarrier and a third input, from the frequency-determining block (318), which defines the frequency, including in some cases all three frequency dimensions, of the component being processed.

The frequency input enables certain frequencies to be treated differently, in particular, different frequencies within the horizontal chrominance band can be treated differently in dependence upon all or any of their three dimensional frequency components. The look-up-table can have different "pages" corresponding to different frequencies or frequency ranges of the component being processed. For example, the frequencies (*a*) and (*b*) in Figure 2 can be regarded as sources of cross-colour and their magnitudes heavily attenuated.

As well as enabling frequency-dependant behaviour, the look-up-table enables an arbitrary function of the amplitudes of the two components to be used to decide the magnitude of the component to be passed to the inverse FFT (310).

An example of a suitable function is shown in Figure 4. This figure shows a contour plot of the table output for various magnitudes of the frequency being processed and the equivalent "subcarrier reflected" frequency component.

It can be seen that where the two components have substantially equal amplitude, the output corresponds to the amplitude of the component being processed. However, where the amplitudes are significantly different, the table output is zero. Between these two regions the output smoothly varies between these two values.

The use of a function which includes the frequency makes it feasible to decode NTSC signals; this is not considered possible in the prior art. In this case a suitable block of pixels for the FFT is 16 pixels horizontally by 16 lines vertically by 4 fields.

Figure 5 shows the vertical/temporal structure of NTSC chrominance. In the same way as shown in Figure 2, the frequency (x) will occur simultaneously with the frequency (w) when (x) is due to true chrominance. However, the frequencies which (due to the spectral repeat) are inherently symmetrical about colour subcarrier are much more troublesome than in the PAL case.

Consider the frequency (o). This is at the origin of the vertical/temporal plane and corresponds to a stationary pattern of fine vertical stripes. It repeats symmetrically with respect to subcarrier and thus, in the case of naive application of the prior art, it would be a potent source of fine cross-colour.

The frequency (d) corresponds to a stationary diagonal pattern (with twice the vertical frequency of colour subcarrier) and would also be a source of cross-colour. Although most picture sources would be pre-filtered to avoid this frequency (because it would be heavily aliassed) it is undesirable for stationary detail to contribute cross-colour.

It is therefore possible to use the decoder of Figure 3 to decode NTSC by arranging for frequency components close to the positions (o) and (d) in Figure 5 to be attenuated. This is done by programming the look-up-table to give negligible output at these frequencies. A suitable method of generating the table contents is to "train" the table by decoding material for which the original un-coded RGB or YUV components are available, and optimising the table to minimise the errors in the decoded output.

The greater likelihood in NTSC of the same sideband frequency resulting from the two baseband chrominance components means that the variation of the look-up-table response with respect to frequency will be greater than in the case of a PAL decoder.

An example of another aspect of the invention, in which the processing is carried out on demodulated chrominance signals, will now be described.

A decoder according to this aspect of the invention is shown in Figure 6. A composite digital input (601), which may be sampled at any convenient frequency (for example an orthogonal, line-locked sampling frequency) is input to a simple chrominance demodulator (617) which outputs in-phase and quadrature baseband chrominance components. In the case of PAL, the V-axis demodulator should not be reversed on alternate lines. The bandwidth of these demodulated components is made sufficiently wide to ensure that all of the chrominance band is included. These demodulated components will, of course, include cross-colour.

In order to carry out the demodulation it is necessary to represent the colour subcarrier in terms of samples at the video sample rate, and to lock the phase of the demodulating subcarrier to the reference burst of the video input. Known techniques, including "ratio counting", can be used.

The demodulated components are remodulated (619), using the identical carriers that were used for demodulation, and subtracted (620) from the composite input to give a signal which contains only luminance.

The two demodulated components are divided into overlapping blocks (602) and windowed (603) in the same way as in Figures 1 and 3. Each block is applied to a complex, three-dimensional FFT (604), which treats the two components as real and imaginary parts of a complex variable. The resulting frequency components are

processed in the same way as described above by the blocks (605), (606), (607), (608) and (609) so as to identify symmetrical components and pass them to the inverse FFT (610).

Because the signal has been demodulated, the horizontal frequency which corresponds to colour subcarrier will be zero, and so the determination of horizontal frequency symmetry requires the use of phase information. This is possible because the FFT (604) processes the signal as a complex variable. The vertical and temporal processing can be similar to that described above.

The real and imaginary outputs of the inverse FFT (610) are windowed (611), and the blocks are combined (612) to give two, cross-colour free, colour difference signals (616). In the case of PAL, the V-axis component must be reversed on alternate lines because this was not done at the demodulation stage.

This "clean" chrominance is subtracted (613) (making due allowance for processing delays) from the unprocessed, demodulated chrominance to give baseband cross-colour. This is remodulated (621), onto the same carriers that were used for the demodulation, to give true luminance. This luminance is added (622) (in the correct phase and appropriately timed) to the output of the subtractor (620). The result is a cross-luminance free, full bandwidth luminance output (614).

The decoder structure of Figure 6 may be used for PAL or NTSC, the only essential differences are the generation of the appropriate subcarrier for demodulation and remodulation, the look-up-table to separate chrominance and luminance, and the alternate line phase reversal of the V-component for PAL.

The decoders described so far have been "complementary", that is to say no input frequencies are lost, they are either processed in the luminance channel or the chrominance channel, and the sum of the chrominance and luminance frequency responses is unity. This ensures theoretical reversibility of the decoding process.

If reversibility is not a requirement, it can be advantageous to optimise the chrominance and luminance responses independently of each other. Figure 7 shows a decoder allowing this possibility.

Referring to Figure 7, it will be seen that there is some similarity with the decoder of Figure 3 (the reference numerals of corresponding functional blocks differ only in the first digit). The difference is that the look-up-table (708) has two outputs, one controlling the luminance response, and the other controlling the chrominance response. There are two separate processing chains (709C to 712C, and 709Y to 712Y), which convert the unit-amplitude frequency components from the divider 706 to luminance and chrominance signals.

The look-up-table 708 can be considered as two separate tables with common inputs, one table producing a luminance amplitude control signal for the multiplier (709Y), and the other producing a chrominance amplitude control signal for the multiplier (709C). The multipliers control the magnitudes of the frequency components input to respective inverse FFT stages (710Y) and (710C).

Figure 8 shows an example of how the luminance amplitude control signal depends on the table inputs for a table "page" close to subcarrier frequency. Where the frequency component being processed is similar in amplitude to the corresponding "reflected" component, the output from the table is zero. Where the two frequency components have significantly different amplitudes, the table output corresponds to

the amplitude of the frequency component being processed. Between these conditions the table output varies smoothly between these two states. This response is the "complement" of the response shown in Figure 4.

Figure 9 shows the chrominance amplitude control signal for a similar region of the table. As the chrominance table is not constrained by the needs of the luminance channel, a response which corrects for distortion of the chrominance can be implemented. Where the frequency component and its reflection are nearly equal in magnitude, the output is equal to the average of the two amplitudes, otherwise the response is similar to that shown in Figure 4. This averaging can eliminate the U/V crosstalk which results from unwanted attenuation of the upper chrominance sidebands by filters in the transmission chain prior to the decoder.

Although the U/V crosstalk is eliminated the chrominance resolution is degraded. Figure 10 shows another chrominance look-up-table function, which restores the lost chrominance resolution. Here the frequency input to the table is used to determine whether the frequency component being processed is an upper or lower chrominance sideband (i.e. whether the signal frequency corresponding to the spatial frequency is higher or lower than that of the unmodulated subcarrier frequency). When the frequency being processed corresponds to an upper sideband, and its amplitude is slightly less than that of the corresponding lower sideband, the table output corresponds to the amplitude of the respective lower sideband. When the frequency input to the table shows that a lower chrominance sideband may be being processed, a response as shown in Figure 4 is used. In this way the high frequency chrominance loss is corrected as well as the U/V crosstalk.

A suitable method of generating the table is to "train" it as described above, using composite material which has suffered a range of sideband losses.

The chrominance processing methods of Figures 9 and 10 are not appropriate for the decoders of Figures 3 or 6 because the modified chrominance would not cancel the input chrominance and cross-luminance would result. However, the decoder of Figure 6 can be modified to include a separate luminance path as shown in Figure 11. Those elements of Figure 11 which correspond to Figure 6 have been given similar reference numerals; the (6*) being replaced by (11*). The look-up-table (1108) has separate outputs to control the chrominance and luminance responses in the same way as the decoder of Figure 7.

It has been explained that different frequencies can address different pages of the look-up-table. Other parameters can be used instead of, or as well as, frequency. Vertical, horizontal or temporal signal-differences can be used to determine the page to be used. The transform may use less than three frequency dimensions, for example the temporal dimension may be omitted and reliance placed upon signal-differences to identify movement in the image being decoded.

It must be recognised that examples of the invention have been described here and that the skilled person will be able to implement it in other ways which fall within the concept which has been described.

Claims

1. A method of separating the chrominance and luminance of a composite colour television signal by comparing each of a set of first frequency components of the signal with a respective second frequency component of the signal, each second component having a frequency difference from the colour subcarrier equal and opposite to the frequency difference from the colour subcarrier of the associated first frequency component, characterised in that respective comparisons differ in dependence upon the frequency of the first frequency component.

2. A method according to Claim 1 in which the comparisons differ in dependence upon the horizontal spatial frequency of the said first frequency component.

3. A method according to Claim 1 in which the comparisons differ in dependence upon the vertical spatial frequency of the said first frequency component.

4. A method according to Claim 1 in which the comparisons differ in dependence upon the temporal frequency of the said first frequency component.

5. A method according to Claim 1 in which the comparisons differ in dependence upon horizontal, vertical or temporal differences of a composite signal.

6. A method according to Claim 1 in which the comparisons differ in dependence upon horizontal, vertical or temporal differences derived from the output of a chrominance demodulator.

7. A method of separating the chrominance and luminance components of a composite colour television signal by comparing a first frequency component of the signal with a second frequency component of the signal, the second component having a frequency difference from the colour subcarrier equal and opposite to the frequency difference of the first frequency component from the colour subcarrier, characterised in that the comparison is made by processing demodulated, baseband chrominance signals.

8. A method of decoding a composite NTSC signal according to any of the preceding claims.

9. A method of decoding a composite colour television signal wherein distortion of the said signal is corrected characterised in that an upper chrominance sideband is identified and its amplitude corrected by making it equal to the amplitude of the corresponding lower chrominance sideband.

10. A method according to Claim 9 in which the corresponding lower sideband is identified in terms of its horizontal spatial, vertical spatial and temporal frequency.

11. A method of processing a television signal according to any of the preceding claims wherein the signal is sampled at an integer multiple of the line frequency.

Figure 1: Prior Art PAL Decoder

Figure 2. Vertical/Temporal spectrum - PAL

Figure 3: Composite Decoder

3/11

Figure 4. Look-up-Table Contour Plot

Figure 5. Vertical/Temporal spectrum: NTSC

Figure 6. Baseband Decoder

Figure 7: Non-Complementary Decoder

Figure 8: Luminance LUT - Example

Figure 9: Chrominance LUT - Example

Large ratios treated as luminance
(LUT output = 0)

Contours of LUT output

Nearly equal magnitudes treated as chrominance (LUT output = average of inputs)

Small ratios treated as luminance
(LUT output = 0)

Magnitude of frequency bin

Magnitude of reflected frequency bin


Figure 10: HF Loss correction

Figure 11. Baseband Non-Complementary Decoder